

## AMENDMENTS TO THE CLAIMS

Claim 1 (Original): A method of forming a photo sensor in a photo diode formed on a semiconductor wafer, a surface  
5 of the semiconductor comprising a substrate with first-type dopants, and an insulating layer positioned on a surface of the substrate and surrounding the photo sensor, the method comprising:

performing a first ion implantation process utilizing  
10 second-type dopants to form a plurality of first doped regions on a surface of the photo sensor; and

performing a second ion implantation process utilizing second-type dopants to form a second doped region on the surface of the photo sensor, and the second  
15 doped region being overlapped with a partial region of each of the first doped regions.

Claim 2 (original): The method of claim 1 wherein the dopants in the first doped regions and in the second doped  
20 region interact with neighboring substrate to form a plurality of depletion regions.

Claim 3 (original): The method of claim 1 wherein the first-type dopants are N-type, and the second-type  
25 dopants are P-type.

Claim 4 (original): The method of claim 1 wherein the first-type dopants are P-type, and the second-type  
dopants are N-type.

30

Claim 5 (original): The method of claim 1 wherein the substrate further comprises an epitaxial silicon layer, and each of the first doped regions and the second doped region are formed inside the epitaxial silicon layer.

5

Claim 6 (original): The method of claim 1 wherein a dopant density of the first ion implantation process is less than a dopant density of the second ion implantation process.

10

Claim 7 (original): The method of claim 1 wherein the surface of the semiconductor wafer further comprises a logic circuit region, and the second ion implantation process forms at least a lightly doped drain (LDD) within the logic circuit region.

15

Claim 8 (original): The method of claim 1 wherein the method further comprises an annealing process for driving-in the dopants in the second doped region.

20

Claim 9 (original): The method of claim 1 wherein each of the depletion regions formed between the neighboring first doped regions is a complete depletion region, and a capacitance of each of the depletion regions is approximately equal to zero for increasing a sensing area, decreasing dark current, and further increasing photo current and photon conversion gain.

25

Claim 10 (original): The method of claim 1 wherein the second doped region is utilized to be a conducting wire

30

of the photo sensor.

Claims 11-19 (Canceled)